RIDGE FLOODLIGHT

LUMIO


RIDGE 10 - 10W, 4000K IP65 Floodlight - Black
RIDGE 20 - 20W, 4000K IP65 Floodlight - Black
RIDGE 30 - 30W, 4000K IP65 Floodlight - Black
RIDGE 50 - 50W, 4000K IP65 Floodlight - Black

SAFETY INFORMATION


Read instructions carefully before installation. Failure to follow instructions may result in electric shock, fire and/or serious injury.

- Electrical appliances should be installed by a licensed electrician.
- Before commencing installation turn off and isolate the electrical supply.
- No user serviceable / replaceable parts inside.
- Do not attempt to service other parts of the unit as this will void the warranty.
- The external flexible cable or cord of this luminaire cannot be replaced; if the cord is damaged, the luminaire shall be destroyed.
- The light source of this luminaire is not replaceable; when the light source reaches its end of life the whole luminaire shall be replaced.
- Do not mount at a height of more than 3 metres.
- Do not jet wash as the floodlight is not rated for high pressure jets of water and may be damaged.
- Ensure the floodlight is adequately fixed to support the floodlight weight and hold it rigidly.
- Do not stare at the operating light source.
- To reduce the risk of strangulation the flexible wiring connected to this luminaire shall be effectively fixed to the wall if the wiring is within arms reach.


Product Dimensions




14986



14987



14988



14989

Product Specifications

Voltage		220-240V~50Hz
Light colour options		Cool White
Colour temperature		4000K
Lumen output	10W	1100lm
	20W	2200lm
	30W	3300lm
	50W	5500lm
Working temperature		-10°C to 40°C
Colour rendering index		>80
Beam angle		110°
Dimmable		No
IP Rating		IP65
IK Rating		IK05
Electrical classification		Class 1
Wiring		Flex and Plug 1m
Mounting type		Surface Mount
Maximum mounting height		3m
Warranty		3 Years


Product Range


Code	SKU	Finish	Wattage
1128209	14986	Black	10W
1128273	14987	Black	20W
1128231	14988	Black	30W
1128272	14989	Black	50W


Installation Steps


Remove the product from the box and inspect it for any damage. If the product is satisfactory, proceed with the installation


1. Isolate the mains power supply before commencing installation of the floodlight.
2. Position the floodlight in your desired position. Mark out the fixing points using the floodlight handle and a pen/pencil.
3. Drill fixing holes according to your chosen fixing method. Mount in position. Fixings are not supplied.
4. Adjust the floodlight head towards the area to be illuminated and lock off using the two clamping bolts.
5. Restore the mains power supply, switch on and test for correct operation.











Warranty

This gives you benefits that are additional to other rights and remedies that you may have pursuant to other laws relating to the Lumio lighting products. Those laws include the Australian Consumer Law and the New Zealand Consumer Law.

Our goods come with guarantees that cannot be excluded under the Australian Consumer Law or the New Zealand Consumer Law. You are entitled to a replacement or refund for a major failure and compensation for any other reasonably foreseeable loss or damage. You are also entitled to have the goods repaired or warranty replaced if the goods fail to be of acceptable quality and the failure does not amount to a major failure.

Nothing in this warranty is to be interpreted as excluding, restricting or modifying any law or statute applicable to the supply of Lumio products which cannot be excluded, restricted or modified by the Australian Consumer Law or the New Zealand Consumer Law (where applicable).

If you think your Lumio product is defective, you can choose to make a claim under:
1. The Australian Consumer Law in Australia;
2. The New Zealand Consumer Law in New Zealand; and/or
3. This warranty, as may be applicable.

Subject to the terms of this contractual warranty, if your Lumio products are defective, we will (at our election) repair or replace the Lumio products. Once we make this election (and take the relevant action), we will have honoured our obligations under this contractual warranty.

Our total liability under this warranty is limited to the cost of repair or replacement of the defective product (at our election). We otherwise exclude all liability in relation to the product to the fullest extent permitted by law (noting our comments above regarding the Australian Consumer Law and any other rights or remedies you may have).

Lumio warrants that it will remedy premature product failure and defects caused by faulty materials or workmanship in Lumio lighting products as follows:

Product Type	Warranty	Remedy
General Lighting (unless otherwise stated)	3Yr	Lumio products labelled 'return to base' are remedied at our own premises (or agent's premises). This means that you are responsible for returning the Product to us for repair, replacement or refund, and collecting the Lumio product from us once it has been repaired or replaced (at our discretion).
Emergency Lighting & Exits	3Yr	
Accessories and Batteries	1Yr	

All warranty periods apply from date of purchase. Date of purchase means the date that you purchased the Lumio product from a Lumio authorised retailer, unless marked otherwise.

For this warranty to apply, you must:

a. Have purchased the Lumio product from an authorised retailer in Australia or New Zealand;
b. Follow the manufacturer's instructions applicable to the Lumio products;
c. Follow the Industry Standards for installation and usage applicable to the Lumio products (if any);
d. Follow any other written or verbal instructions for installation, operation, care, repair and maintenance of the Lumio products. Those directions may be supplied with the Lumio products, printed on the labels, packaging or operation manuals, published on the Lumio website or otherwise published from time to time; and
e. Follow the claims procedure for making a warranty claim as outlined in this document

Within 7 days of any defect arising (or the day that you should have reasonably become aware of the defect), you must either return the defective goods to the point of sale for refund, or notify Lumio of the defect in writing through our claims processes.

What must be included in the warranty claim:

- proof of purchase (if available) date and place of purchase
- the item number/ code of the returned product and the number of items claimed
- the reason for the claim and written description of the defect (including photographs where reasonably possible)
- any information provided by the customer
- your written assurance that the Lumio products have not been:
  - incorrectly assembled or installed;
  - incorrectly operated or used or maintained;
  - incorrectly repaired or modified;
  - exposed to abnormal conditions; or
  - damaged by you (due to negligence or otherwise)
- request for labour allowance rates (if applicable)

To lodge a warranty claim, please visit our website at lumio.com.au/warranty

Alternatively you can make a claim directly via email at **sales@lumio.com.au** or telephone **1300 438 658**.

Once we receive your warranty claim, we will contact you within 2 working days.

This warranty does not apply to loss or damage caused by wear and tear, misuse, incorrect installation or operation, failure to clean and maintain, incorrect voltage or non-authorised electrical connections, adverse external conditions (such as power surges and dips, acts of God, exposure to heat, corrosion, insect or vermin infestation), use of non-authorised or defective parts or globes, or to items that have been repaired by a person other than us or a repairer approved by us.

Images are for illustrative purposes only.
Due to changes in industry standards and continual product development, product specifications are subject to change without notice.

For sales and product information telephone
Customer Service: 1300 438 658
New Zealand: 0800 235 867

Website: lumio.com.au